# Load pin Up to 10,000 kN Model F5802

WIKA data sheet FO 51.55



## **Applications**

- Crane systems and hoists
- Industrial weighing technology
- Machine building and plant construction
- Manufacturing automation

## **Special features**

- Measuring ranges 20 ... 10,000 kN [204 tf ... 101,972 tf]
- Corrosion-resistant stainless steel version
- Existing non-measuring bolts are simply replaced by the measuring axes
- For overload protection in cranes and hoists
- Good reproducibility, easy installation



#### Load pin, model F5802

For further approvals see page 2

## Description

Load pins of the model F5802 are suitable for static and dynamic measuring tasks as a replacement for non-measuring bolts. They serve for determining tension and/or compression forces under harsh operating conditions.

The load pins are very often used in hoists and crane systems, e.g. used in construction cranes or in port and offshore cranes, as well as in the field of industrial weighing technology and special machine construction. There they are installed in particular in deflection pulleys, cable winches, fork or roller bearings.

Load pins of this model serve as reliable overload protection in mechanical and plant engineering.

The corresponding technical and regional approvals of these force transducers are, of course, available as options.

The load pins are made of high-strength, corrosion resistant 1.4542 stainless steel, the properties of which are ideal for the application areas.

As output signals, the common active current and voltage outputs are available (4  $\dots$  20 mA, 0  $\dots$  10 V). Redundant output signals and CANopen<sup>®</sup> protocols are also possible.







# Technical data in accordance with VDI/VDE/DKD 2638

Model	F5802
Rated force F <sub>nom</sub> kN [tf]	20 10,000 [204 101,972]
Relative linearity error d <sub>lin</sub> d <sub>lin</sub> <sup>1)</sup>	0.5 % 1 % F <sub>nom</sub>
Relative Umkehrspanne v	0.5 % 1 % F <sub>nom</sub>
Relative repeatability error in unchanged mounting position $\mathbf{b}_{\mathrm{rg}}$	0.5 % 1 % F <sub>nom</sub>
Temperature effect on	
characteristic value TK <sub>C</sub>	0.2 % Fnom /10 K
zero signal TK <sub>0</sub>	0.2 % Fnom /10 K
Force limit F <sub>L</sub>	150 % F <sub>nom</sub>
Breaking force F <sub>B</sub>	300 % F <sub>nom</sub>
Material of measuring device	Corrosion-resistant stainless steel
Rated temperature B <sub>T, nom</sub>	-10 +40 °C [14 +104 °F]
Operating temperature B <sub>T, G</sub>	-20 +80 °C [-4 +176 °F]
Electrical connection	M12 x 1, 4-pin or 5-pin
Output signal (rated output) C <sub>nom</sub>	<ul> <li>4 20 mA, 2-wire</li> <li>4 20 mA, 3-wire</li> <li>2 x 4 20 mA, redundant</li> <li>DC 0 10 V, 3-wire</li> <li>2 x DC 0 10 V redundant</li> <li>1 2 mV/V</li> <li>CANopen®</li> <li>Protocol in accordance with CiA®301, device profile CiA®404, communication services LSS (CiA®305), configuration of the instrument address and baud rate Sync/Async, Node/ Lifeguarding, heartbeat; zero and span ±10 % adjustable via entries in the object directory <sup>2</sup>)</li> </ul>
Input resistance R <sub>e</sub>	$750 \pm 30 \Omega$
Output resistance R <sub>a</sub>	$700 \pm 5 \Omega$
Isulation resistance R <sub>iS</sub>	≥ 5,000 MΩ
Supply voltage UB	<ul> <li>DC 9 36 V for current output</li> <li>DC 13 36 V for voltage output</li> <li>DC 5 10 V for mV/V</li> <li>DC 9 36 V for CANopen<sup>®</sup></li> </ul>
Ingress protection (acc. to IEC/EN 60529)	IP67

<sup>1)</sup> Relative linearity error accordance with VDI/VDE/DKD 2638 chapter 3.2.6.


## **Approval**

Logo	Description	Region
CE	EU declaration of conformity  ■ EMC directive  ■ RoHS directive	European Union
EAC	EAC EMC directive	Eurasian Economic Community

<sup>→</sup> Approvals and certificates, see website.

<sup>2)</sup> Protocol in accordance with CiA®301, device profile CiA®404, communication service LSS (CiA®305) CANopen® and CiA® are registered community trademarks of CAN® in Automation e. V.

# Dimensions/mounting situation of the load pin




Exemplary illustration.


Dimensioning: The customer-specific load pin drawing of the respective order number has priority.

# Pin assignment cable

Electrical connection		
Supply voltage +	Exc+	Red
Supply voltage -	Exc-	Black
Signal +	Sig+	Green
Signal -	Sig-	White
Shield ⊕	Shield	Yellow-green



#### Output signal 1 ... 2 mV/V Connector M12 x 1, 4-pin or 5-pin





# Pin assignment of analogue output


#### Abbreviations, definitions

Signal	Description
UB	Voltage source for sensor
UB+	Sensor-supply voltage (+)
UB-	Sensor-supply voltage (-)
S+	Output signal (+)
S-	Output signal (-)
0V	0V-Potential

Signal	Description
A	Ammeter
V	Voltmeter
+	Voltage source
~-	Switch
<b>(4)</b>	Shield (grounding)

#### Output 4 ... 20 mA, 2-wire

Connector M12 x 1, 5-pin




Signal	4 20 mA, 2-wire	Cable colour
UB+/S+	1	Brown
0V/S-	3	Black
Shield (=)	Case / connector	-

Cable colours only apply when using the WIKA standard cable, e.g. order number 14259454

#### Output 4 ... 20 mA, 3-wire

Connector M12 x 1, 5-pin




Signal	4 20 mA, 3-wire	Cable colour
UB+	1	Brown
S+	4	Black
0V/S-	3	Blue
Shield 🖶	Case / connector	-

Cable colours only apply when using the WIKA standard cable, e.g. order number: 14259454

#### Output 0...10 V, 3-wire

Connector M12 x 1, 5-pin



Signal	0 10 V, 3-wire	Cable colour
UB+	1	Brown
S+	4	Black
0V/S-	3	Blue
Shield 🖶	Case / connector	-

# Pin assignment with signal jump


#### Abbreviations, definitions

Signal	Description
UB	Voltage source for sensor
UB+	Sensor-supply voltage (+)
UB-	Sensor-supply voltage (-)
UR	Voltage source for den signal jump
UR+	Signal jump-supply voltage (+)
UR-	Signal jump-supply voltage (-)
S+	Output signal (+)
S-	Output signal (-)
0V	0V-Potential

Signal	Description
A	Ammeter
V	Voltmeter
+	Voltage source
<b>¬</b> -	Switch
<b>=</b>	Shield (grounding)

## Output 4 ... 20 mA, 2-wire

Circular connector M12 x 1, 4-pin




Signal	4 20 mA, 2-wire	Cable colour
UB+/S+	1	Brown
0V/S-	3	Blue
UR+	2	White
UR-	4	Black
Shield <b>⊕</b>	Case / connector	-

Cable colours only apply when using the WIKA standard cable, e.g. order number 14259454

## Output 4 ... 20 mA, 3-wire

Circular connector M12 x 1, 4-pin




Signal	4 20 mA, 3-wire	Cable colour
UB+	1	Brown
0V/S-	3	Blue
UR+	2	White
UR-	3	Blue
S+	4	Black
Shield ⊕	Case / Connector	-

Cable colours only apply when using the WIKA standard cable, e.g. order number 14259454

#### Output 0...10 V, 3-wire

Circular connector M12 x 1, 4-pin




Signal	0 10 V, 3-wire	Cable colour
UB+	1	Brown
0V/S-	3	Blue
UR+	2	White
UR-	3	Blue
S+	4	Black
Shield 🖶	Case / Connector	-

# Pin assignment for CANopen®

#### Abbreviations, definitions

Signal	Description
CAN-SHLD, Shield	Shield
CAN-V+	External positive voltage supply for the supply of the sensor
CAN-GND	External 0V Potential for the supply of the sensor
CAN-High	CAN_H Bus line (dominant high)
CAN-Low	CAN_L Bus line (dominant low)


# Output CANopen® in according to CiA®303-1 Circular connector M12 x 1, 5-pin



Signal	Pin	Cable colour
CAN-SHLD, Shield	1 / Case / connector	Brown
CAN-V+	2	Blue
CAN-GND	3	White
CAN-High	4	Blue
CAN-Low	5	Black

## Short description of the signal jump electronics

Amplifier 4 ... 20 mA or 0 ... 10 V for signal jump applications with 2-channel computer control.



With these force transducers, four variable resistors (R1 ... R4) are connected together to form a Wheatstone bridge. When the measuring body deforms, the opposing resistors are stretched or compressed in the same way. This leads to a detuning of the bridge and a diagonal voltage U0.


The test resistor R7 is now important in connection with checking the subsequent amplifier circuit and the subsequent signal paths. This is switched parallel to the resistor R5 via the relay contact (a) as soon as the excitation voltage Ur of the relay A is present. The connection of the resistor R7 causes a defined, always constant, detuning of the zero point (diagonal voltage) of the Wheatstone bridge.

An external safety control system independent of the force transducer must monitor the safe functioning of the force transducer. The functional test with a signal jump of 4 mA / 2 V is executed at an interval of 24 hours. The safety control system activates the relay A, thus changing the output signal of the force transducer in a defined manner.

If the expected change in the output signal occurs, it can be assumed that the entire signal path from the Wheatstone bridge via the amplifier through to the output is functioning correctly. If this does not occur, then it can be concluded that there is a error in the signal path.

Furthermore, the measuring signal should be checked by the safety controller for min. (A) and max. (B) signal values in order to detect any cable breaks or short circuits that may occur.

The default setting of the force transducers with a current output of 4 ... 20 mA for overload detection is, for example:



With a fixed signal jump of, for example, 4 mA, the test cycle can then be triggered, in any operating state, by activating the test relay. The upper measuring range limit of 20 mA will never be reached and thus the checking of the signal jump is enabled.

#### **Accessories**

Connector M12 x 1, model EZE53 with moulded cable							
Model	Description	Temperature range	Cable diameter	Cable colour	Order number		
	Straight version, cut to length, 4-pin, PUR cable, UL listed, IP67	-20 +80 °C [-4 +176 °F]	Ø 4.75 mm 5.7 mm [Ø 0.18 in 0.22 in]	2 m [6.6 ft]	14259451		
				5 m [16.4 ft]	14259453		
				10 m [32.8 ft]	14259454		
40	Straight version, cut to length, 5-pin, PUR cable, UL listed, IP67	-20 +80 °C [-4 +176 °F]	Ø 4.75 mm 5.7 mm [Ø 0.18 in 0.22 in]	2 m [6.6 ft]	14259458		
				5 m [16.4 ft]	79100672		
				10 m [32.8 ft]	14259472		
	Angled version, cut to length, 4-pin, PUR cable, UL listed, IP67	-20 +80 °C [-4 +176 °F]	Ø 5.05 mm 6 mm [Ø 0.2 in 0.24 in]	2 m [6.6 ft]	14259452		
				5 m [16.4 ft]	14293481		
				10 m [32.8 ft]	14259455		
	Angled version, cut to length, 5-pin, PUR cable, UL listed, IP67	-20 +80 °C [-4 +176 °F]	Ø 5.05 mm 6 mm [Ø 0.2 in 0.24 in]	2 m [6.6 ft]	79101493		
				5 m [16.4 ft]	79100686		
				10 m [32.8 ft]	On request		

Other cable lengths and cable types are available on request.

WIKA accessories can be found online at www.wika.com.

#### **Ordering information**

WIKA data sheet FO 51.55 · 02/2024

Model / Rated force / Relative linearity error / Temperature range / Output signal / Electrical connection / Approvals, certificates / Pin assignment / Accessories

© 06/2022 WIKA Alexander Wiegand SE & Co. KG, all rights reserved.

The specifications given in this document represent the state of engineering at the time of publishing.

We reserve the right to make modifications to the specifications and materials.

In the case of a different interpretation of the translated and the English data sheet, the English wording shall prevail.

WIKA

Page 8 of 8